

LED LIGHT + WIFI JBL LOUDSPEAKER

- Combine and control several lights – flexible usage
- Light, sound and music settings via the app
- Supports DLNA, Airplay and the most popular streaming services

Lights on, party!

Simply integrate Sengled Pulse Flex (which has speakers made by JBL) into your home WIFI network. By using the free app you can easily dim the light steplessly and create individually controllable groups with multiple bulbs. The result is a multi-room environment in which you can play back several sources at the same time. You can easily start streaming music by using popular apps such as Spotify or Deezer and just switch it over to the bulbs. Your mobile is then free to use for whatever you wish. And to maximise the fun you can also use Pulse Flex in any E27 socket outdoors!

Technical Data

Model number:	C02-BR30EAE27 / B22
Energy supply:	220-240V, 50/60Hz
Lamp base:	E27, B22
Energy consumption:	10W (rated), 15W (LED + speaker)
Operating temperature:	0°C ~ +35°C
Luminous flux:	470 lumen
Colour temperature:	2700 kelvin
Colour-rendering index:	80
Beam angle:	100°
Loudspeaker:	13W JBL
Frequency response:	100Hz - 20kHz
Wireless connection:	2.4GHz & 5GHz (Wi-Fi)
System Wireless Latency:	< 1ms
Transmitter power:	15dBm (max.)
Protection class:	IP54
Housing color:	silver, champagne, white
Dimensions:	161mm (height) x 95mm (diameter)
Weight:	380g (approx.)



JBL